## 

Fire detection and evacuation solutions that save lives.

## **Tone List - Graphical**

No.Name	Switch (23456)	Alert Frequency	Alert Graphical	Evacuate Frequency	Evacuate Graphical
1 LF Sweep (Cranford Sweep)	11111	800-1000Hz swept every 500ms (2Hz)	1000Hz 800Hz 4300ms	800Hz continuous	800Hz
2 Alternative Warble BS	11110	800Hz for 250ms, then 960Hz for 250ms	1000Hz	800Hz continuous	800Hz
3 Warble Tone BS	11101	800Hz for 500ms, then 1000Hz for 500ms	1000Hz	800Hz continuous	800Hz
4 Alternative Warble BS	11100	500Hz for 250ms, then 600Hz for 250ms	600Hz	500Hz continuous	500Hz
5 HF Back Up Interrupted	11011	2800Hz for 1000ms, then off for 1000ms	2800Hz 1000ms ► 1000ms ►	2800Hz continuous	2800Hz
6 LF Back Up Alarm	11010	800Hz for 150ms, then off for 150ms	800Hz — Isoms Isoms	800Hz continuous	800Hz
7 HF Back Up Interrupted (Fast)	11001	2800Hz for 150ms, then off for 150ms	2800Hz	800Hz continuous	800Hz
8 LF Continuous Tone BS5839	11000	800Hz continuous	800Hz	800Hz continuous	800Hz
9 Sweep - 1Hz	10111	800-900Hz swept every 1000ms (1Hz)	900Hz	800Hz continuous	800Hz
10 New Zealand (NZS 4512)	10110	420Hz for 625ms, then off for 625m	420Hz	500-1200Hz for 3750ms, then off for 250ms	1200Hz
11 Dutch Sweep	10101	970Hz continuous	970Hz	500-1200Hz for 3500ms, then off for 500ms	1200Hz
12 Analogue Sweep	10100	500-600Hz swept every 500ms (2Hz)	600Hz	500Hz continuous	500Hz
13 Sweep - 3Hz	10011	800-970Hz swept every 333ms (3Hz)	970Hz 800Hz	800Hz continuous	800Hz
14 Alternate HF Slow Sweep	10010	2350-2900Hz swept every 333ms (3Hz)	2900Hz 2350Hz 333ms	2400Hz continuous	2400Hz
15 Fast HF Sweep	10001	2400-2800Hz swept every 143ms (7Hz)	2800Hz _ ///////////////////////////////////	2400Hz continuous	2400Hz
16 US Temporal Pattern LF	10000	950 Hz for 500ms on, 500ms off (x3), then 1500ms off	2400Hz Sooms 500ms 1500ms 1	800Hz continuous	800Hz
17 Interrupted BS	01111	800Hz for 500ms, then off for 500ms	800Hz + 500ms + 500ms +	800Hz continuous	800Hz
18 Australian (AS1670:4-2004)	01110	420Hz for 625ms, then off for 625ms	420Hz + 625ms + 625ms +	500-700Hz 500ms on 500ms off x3 1s off	700Hz
19 Interrupted Medium	01101	1000Hz for 250ms, then off for 250ms	1000Hz ii ii 250ms 250ms 250ms	800Hz continuous	800Hz
20 Australian (AS7240-3)	01100	520Hz for 500ms, then off for 3.5s	500Hz	520Hz 500ms on 500ms off x3 1s off	500Hz 500ms to 1500ms
21 Continuous	01011	1000Hz continuous	1000Hz	1000Hz continuous	1000Hz
22 LF Buzz	01010	800-950Hz swept every 9ms (110Hz)	950Hz =mmmmmmmmmmmmmmmmmmm 800Hz =mmmmmmmmmmmmmmmmmmmmmmmmmmmmmmmmmm	800Hz continuous	800Hz
23 HF Continuous	01001	2800Hz continuous	2800Hz	2800Hz continuous	2800Hz
24 Sweep	01000	800-970Hz swept every 111ms (9Hz)	970Hz- 800Hz	800Hz continuous	800Hz
25 German DIN Tone	00111	1200-500Hz swept every 1000ms (1Hz)	1200Hz	800Hz continuous	800Hz
26 Swedish Fire Signal	00110	660Hz for 150ms, then off for 150ms	660Hz —	660Hz for 150ms, then off for 150ms	660Hz —
27 French Tone AFNOR	00101	554Hz for 100ms, then 440Hz for 400ms	554Hz	800Hz continuous	800Hz
28 Swedish All Clear Signal	00100	660Hz continuous	660Hz	660Hz continuous	660Hz
29 US Temporal Pattern HF	00011	2900Hz for 500ms on, 500ms off (x3), then1500ms off	2900Hz H	2900Hz continuous	2900Hz
30 Siren 2 Way Ramp (Short)	00010	500-1200Hz rising for 250ms, then falling for 250ms	1200Hz 500Hz	800Hz continuous	800Hz
31 FP1063.1-Telecom	00001	800Hz for 250ms, then 970Hz for 250ms	970Hz	800Hz continuous	800Hz
32 Siren 2 Way Ramp (Long)	00000	500-1200Hz rising for 3000ms, then falling for 3000ms	1200Hz	800Hz continuous	800Hz

Note: Tone 20 (default settings) frequencies are set to comply with AS 4428-16:2015.